

NM7010B

No.	COUNT	LOCATION	DESCRIPTION	ASSORTMENT	Mfg.
1	1	CP1	22uF CTYPE(6032) 20% 16V	CAP - TANTAL	
2	1	CP2	10uF ATYPE(3216) 10V	CAP - TANTAL	
3	1	CP3	2.2uF ATYPE(3216) 10V	CAP - TANTAL	
		C1,C5,C6,C7,C9,C10,C11,C13 ,C14,C15,C16,C17,C18,C19,			
4	17	C20,C21,C22	0.1uF 1608 20% 50V	CAP-CHIP	
5	2	C8,C12	20pF 1608 20% 50V	CAP - CHIP	
6	1	D1	1SS181 Switching Diode SOT-23	DIODE	
7	2	JP2,JP1	87089-2816 2X14 28PIN 2mm DIP STRAIGHT	HEADER	MOLEX
8	2	L2,L1	HB-1M1608-121 120R @ 100MHz 2012 0.12R 300mA	BEAD - CHIP	CERATECH
9	1	L3	FI-B2012-472KJP 4.7uH	Inductor - CHIP	CERATECH
10	1	R1	1K 1608 5% 1/10W	RES - CHIP	
11	1	R2	1.5K 1608 5% 1/10W	RES - CHIP	
12	2	R4,R3	200R 1608 5% 1/10W	RES - CHIP	
13	4	R5,R6,R7,R8	51R 1608 1% 1/10W	RES - CHIP	
14	1	R9	5.9K 1608 1% 1/10W	RES - CHIP	
15	2	R10,R11	4.7K 1608 5% 1/10W	RES - CHIP	
16	2	R12,R13	4.7K 3216 CONVEX 5% 50V	RES - CHIP - ARRAY	
17	1	U1	W3150A	IC - TCP/IP	WIZNET
18	1	U2	RTL8201BL LQFP48 PHY	IC - PHY	REALTEK
19	1	U3	LU1T516-43 MAG - JACK	CONNECTOR - RJ45	BOTHHAND
20	1	Y1	ATS25/U 25MHz ATS Holder Type	CRYSTAL	SUNNY
21	1		NM7010B-LF1.2 FR4 1.6T 4LAYER	PRINTED CIRCUIT BOARD	